



International Journal of Social Economics

Empirical study in finite correlation coefficient in two phase estimation

M. Khoshnevisan, F. Kaymarm, H.P. Singh, R. Singh, F. Smarandache,

Article information:

To cite this document:

M. Khoshnevisan, F. Kaymarm, H.P. Singh, R. Singh, F. Smarandache, (2004) "Empirical study in finite correlation coefficient in two phase estimation", International Journal of Social Economics, Vol. 31 Issue: 10, pp.890-902, <https://doi.org/10.1108/03068290410555381>

Permanent link to this document:

<https://doi.org/10.1108/03068290410555381>

Downloaded on: 27 April 2018, At: 08:14 (PT)

References: this document contains references to 18 other documents.

To copy this document: permissions@emeraldinsight.com

The fulltext of this document has been downloaded 1046 times since 2006*

Users who downloaded this article also downloaded:

(2011), "A new space-time correlation coefficient and its comparison with Moran's Index on evaluation", Management Decision, Vol. 49 Iss 9 pp. 1426-1443 <<https://doi.org/10.1108/00251741111173925>><https://doi.org/10.1108/00251741111173925>

(1973), "A WEIGHTED RANK CORRELATION COEFFICIENT FOR THE COMPARISON OF RELEVANCE JUDGEMENTS", Journal of Documentation, Vol. 29 Iss 4 pp. 380-389 <<https://doi.org/10.1108/eb026564>><https://doi.org/10.1108/eb026564>

Access to this document was granted through an Emerald subscription provided by

For Authors

If you would like to write for this, or any other Emerald publication, then please use our Emerald for Authors service information about how to choose which publication to write for and submission guidelines are available for all. Please visit www.emeraldinsight.com/authors for more information.

About Emerald www.emeraldinsight.com

Emerald is a global publisher linking research and practice to the benefit of society. The company manages a portfolio of more than 290 journals and over 2,350 books and book series volumes, as well as providing an extensive range of online products and additional customer resources and services.

Emerald is both COUNTER 4 and TRANSFER compliant. The organization is a partner of the Committee on Publication Ethics (COPE) and also works with Portico and the LOCKSS initiative for digital archive preservation.

*Related content and download information correct at time of download.



Empirical study in finite correlation coefficient in two phase estimation

M. Khoshnevisan

School of Accounting and Finance, Griffith University, Australia

F. Kaymarm

Department of Mechanical Engineering, Massachusetts Institute of Technology, USA; currently at Sharif University, Tehran, Iran

H.P. Singh and R. Singh

Department of Mathematics and Statistics, Vikram University, India

F. Smarandache

Department of Mathematics, University of New Mexico, Gallup, USA

Keywords Correlation analysis, Variance, Estimation

Abstract This paper proposes a class of estimators for population correlation coefficient when information about the population mean and population variance of one of the variables is not available but information about these parameters of another variable (auxiliary) is available, in two phase sampling and analyzes its properties. Optimum estimator in the class is identified with its variance formula. The estimators of the class involve unknown constants whose optimum values depend on unknown population parameters. In earlier research it has been shown that when these population parameters are replaced by their consistent estimates the resulting class of estimators has the same asymptotic variance as that of optimum estimator. An empirical study is carried out to demonstrate the performance of the constructed estimators.

1. Introduction

Consider a finite population $U = \{1, 2, \dots, i, \dots, N\}$. Let y and x be the study and auxiliary variables taking values y_i and x_i , respectively, for the i th unit. The correlation coefficient between y and x is defined by

$$\rho_{yx} = S_{yx} / (S_y S_x) \quad (1.1)$$

where

$$S_{yx} = (N - 1)^{-1} \sum_{i=1}^N (y_i - \bar{Y})(x_i - \bar{X}),$$

$$S_x^2 = (N - 1)^{-1} \sum_{i=1}^N (x_i - \bar{X})^2,$$

$$S_y^2 = (N - 1)^{-1} \sum_{i=1}^N (y_i - \bar{Y})^2,$$



$$\bar{X} = N^{-1} \sum_{i=1}^N x_i,$$

$$\bar{Y} = N^{-1} \sum_{i=1}^N y_i.$$

Based on a simple random sample of size n drawn without replacement, (x_i, y_i) , $i = 1, 2, \dots, n$; the usual estimator of ρ_{yx} is the corresponding sample correlation coefficient:

$$r = s_{yx} / (s_x s_y) \tag{1.2}$$

where

$$s_{yx} = (n - 1)^{-1} \sum_{i=1}^n (y_i - \bar{y})(x_i - \bar{x}),$$

$$s_x^2 = (n - 1)^{-1} \sum_{i=1}^n (x_i - \bar{x})^2$$

$$s_y^2 = (n - 1)^{-1} \sum_{i=1}^n (y_i - \bar{y})^2,$$

$$\bar{y} = n^{-1} \sum_{i=1}^n y_i,$$

$$\bar{x} = n^{-1} \sum_{i=1}^n x_i.$$

The problem of estimating ρ_{yx} has been earlier taken up by various authors including Gupta and Singh (1989), Gupta *et al.* (1978, 1979), Koop (1970), Rana (1989), Singh *et al.* (1996) and Wakimoto (1971), in different situations. Srivastava and Jhaji (1986) have further considered the problem of estimating ρ_{yx} in the situations where the information on auxiliary variable x for all units in the population is available. In such situations, they have suggested a class of estimators for ρ_{yx} which utilizes the known values of the population mean \bar{X} and the population variance S_x^2 of the auxiliary variable x .

In this paper, using two-phase sampling mechanism, a class of estimators for ρ_{yx} in the presence of the available knowledge (\bar{Z} and S_z^2) on second auxiliary variable z is considered, when the population mean \bar{X} and population variance S_x^2 of the main auxiliary variable x are not known.

2. The suggested class of estimators

In many situations of practical importance, it may happen that no information is available on the population mean \bar{X} and population variance S_x^2 , we seek to estimate

the population correlation coefficient ρ_{yx} from a sample “s” obtained through a two-phase selection. Allowing simple random sampling without replacement scheme in each phase, the two-phase sampling scheme will be as follows:

- (1) The first phase sample s^* ($s^* \subset U$) of fixed size n_1 , is drawn to observe only x in order to furnish a good estimates of \bar{X} and S_x^2 .
- (2) Given s^* , the second-phase sample s ($s \subset s^*$) of fixed size n is drawn to observe y only.

Let

$$\bar{x} = (1/n) \sum_{i \in s} x_i,$$

$$\bar{y} = (1/n) \sum_{i \in s} y_i,$$

$$\bar{x}^* = (1/n_1) \sum_{i \in s^*} x_i,$$

$$s_x^2 = (n - 1)^{-1} \sum_{i \in s} (x_i - \bar{x})^2,$$

$$s_x^{*2} = (n_1 - 1)^{-1} \sum_{i \in s^*} (x_i - \bar{x}^*)^2.$$

We write $u = \bar{x}/\bar{x}^*$, $v = s_x^2/s_x^{*2}$. Whatever be the sample chosen let (u, v) assume values in a bounded closed convex subset, R , of the two-dimensional real space containing the point $(1, 1)$. Let $h(u, v)$ be a function of u and v such that:

$$h(1, 1) = 1 \tag{2.1}$$

and such that it satisfies the following conditions:

- (1) The function $h(u, v)$ is continuous and bounded in R .
- (2) The first and second partial derivatives of $h(u, v)$ exist and are continuous and bounded in R .

Now one may consider the class of estimators of ρ_{yx} , defined by:

$$\hat{\rho}_{hd} = rh(u, v) \tag{2.2}$$

which is double sampling version of the class of estimators

$$\tilde{r}_t = rf(u^*, v^*)$$

Suggested by Srivastava and Jhaji (1986), where $u^* = \bar{x}/\bar{X}$, $v^* = s_x^2/S_x^2$ and (\bar{X}, S_x^2) are known.

Sometimes even if the population mean \bar{X} and population variance S_x^2 of x are not known, information on a cheaply ascertainable variable z , closely related to x but

compared to x remotely related to y , is available on all units of the population. This type of situation has been briefly discussed by, among others, Chand (1975) and Kiregyera (1980, 1984). Finite correlation coefficient

Following Chand (1975) one may define a chain ratio-type estimator for ρ_{yx} as

$$\hat{\rho}_{1d} = r \left(\frac{\bar{x}^*}{\bar{x}} \right) \left(\frac{\bar{Z}}{\bar{z}^*} \right) \left(\frac{S_x^{*2}}{S_x^2} \right) \left(\frac{S_z^2}{S_z^{*2}} \right) \quad (2.3)$$

where the population mean \bar{Z} and population variance S_z^2 of second auxiliary variable z are known, and

$$\bar{z}^* = (1/n_1) \sum_{i \in s^*} z_i,$$

$$S_z^{*2} = (n_1 - 1)^{-1} \sum_{i \in s^*} (z_i - \bar{z}^*)^2$$

are the sample mean and sample variance of z based on preliminary large sample s^* of size $n_1 (> n)$.

The estimator $\hat{\rho}_{1d}$ in equation (2.3) may be generalized as

$$\hat{\rho}_{2d} = r \left(\frac{\bar{x}}{\bar{x}^*} \right)^{\alpha_1} \left(\frac{S_x^2}{S_x^{*2}} \right)^{\alpha_2} \left(\frac{\bar{z}^*}{\bar{Z}} \right)^{\alpha_3} \left(\frac{S_z^{*2}}{S_z^2} \right)^{\alpha_4} \quad (2.4)$$

where α_i 's ($i = 1, 2, 3, 4$) are suitably chosen constants.

Many other generalization of $\hat{\rho}_{1d}$ is possible. We have, therefore, considered a more general class of ρ_{yx} , from which a number of estimators can be generated.

The proposed generalized estimators for population correlation coefficient ρ_{yx} , is defined by

$$\hat{\rho}_{td} = rt(u, v, w, a) \quad (2.5)$$

where $w = \bar{z}^*/\bar{Z}$, $a = S_z^{*2}/S_z^2$ and $t(u, v, w, a)$ is a function of (u, v, w, a) such that

$$t(1, 1, 1, 1) = 1 \quad (2.6)$$

Satisfying the following conditions:

- (1) Whatever be the samples (s^* and s) chosen, let (u, v, w, a) assume values in a closed convex subset S , of the four-dimensional real space containing the point $P = (1, 1, 1, 1)$.
- (2) In S , the function $t(u, v, w, a)$ is continuous and bounded.
- (3) The first and second order partial derivatives of $t(u, v, w, a)$ exist and are continuous and bounded in S .

To find the bias and variance of $\hat{\rho}_{td}$ we write:

$$s_y^2 = S_y^2(1 + e_1),$$

$$\bar{x} = \bar{X}(1 + e_1),$$

$$\bar{x}^* = \bar{X}(1 + e_1^*),$$

$$s_x^2 = S_x^2(1 + e_2)$$

$$s_x^{*2} = S_x^2(1 + e_2^*),$$

$$\bar{z}^* = \bar{Z}(1 + e_3^*),$$

$$s_z^{*2} = S_z^2(1 + e_4^*),$$

$$s_{yx} = S_{yx}(1 + e_5)$$

such that

$$E(e_0) = E(e_1) = E(e_2) = E(e_5) = 0$$

and

$$E(e_i^*) = 0 \quad \forall \quad i = 1, 2, 3, 4,$$

and ignoring the finite population correction terms, we write to the first degree of approximation:

$$E(e_0^2) = (\delta_{400} - 1)/n, \quad E(e_1^2) = C_x^2/n, \quad E(e_1^{*2}) = C_x^2/n_1, \quad E(e_2^2) = (\delta_{040} - 1)/n,$$

$$E(e_2^{*2}) = (\delta_{040} - 1)/n_1, \quad E(e_3^2) = C_z^2/n_1, \quad E(e_4^{*2}) = (\delta_{004} - 1)/n_1,$$

$$E(e_5^2) = \left\{ \left(\delta_{220} / \rho_{yx}^2 \right) - 1 \right\} / n, \quad E(e_0 e_1) = \delta_{210} C_x / n, \quad E(e_0 e_1^*) = \delta_{210} C_x / n_1,$$

$$E(e_0 e_2) = (\delta_{220} - 1)/n, \quad E(e_0 e_2^*) = (\delta_{220} - 1)/n_1, \quad E(e_0 e_3^*) = \delta_{201} C_z / n_1,$$

$$E(e_0 e_4^*) = (\delta_{202} - 1)/n_1, \quad E(e_0 e_5) = \{ (\delta_{310} / \rho_{yx}) - 1 \} / n,$$

$$E(e_1 e_1^*) = C_x^2 / n_1, \quad E(e_1 e_2) = \delta_{030} C_x / n, \quad E(e_1 e_2^*) = \delta_{030} C_x / n_1,$$

$$E(e_1 e_3^*) = \rho_{xz} C_x C_z / n_1, \quad E(e_1 e_4^*) = \delta_{012} C_x / n_1, \quad E(e_1 e_5) = (\delta_{120} C_x / \rho_{yx}) / n,$$

$$E(e_1^* e_2) = \delta_{030} C_x / n_1, \quad E(e_1^* e_2^*) = \delta_{030} C_x / n_1, \quad E(e_1^* e_3^*) = \rho_{xz} C_x C_z / n_1,$$

$$E(e_1^*e_4^*) = \delta_{012}C_x/n_1, \quad E(e_1^*e_5^*) = (\delta_{120}C_x/\rho_{yx})/n_1,$$

$$E(e_2e_2^*) = (\delta_{040} - 1)/n_1, \quad E(e_2e_3^*) = \delta_{021}C_z/n_1, \quad E(e_2e_4^*) = (\delta_{022} - 1)/n_1,$$

$$E(e_2e_5) = \{(\delta_{130}/\rho_{yx}) - 1\}/n, \quad E(e_2^*e_3^*) = \delta_{021}C_z/n_1,$$

$$E(e_2^*e_4^*) = (\delta_{022} - 1)/n_1, \quad E(e_2^*e_5) = \{(\delta_{130}/\rho_{yx}) - 1\}/n_1,$$

$$E(e_3^*e_4^*) = \delta_{003}C_z/n_1, \quad E(e_3^*e_5) = (\delta_{111}C_z/\rho_{yx})/n_1,$$

$$E(e_4^*e_5) = \{(\delta_{112}/\rho_{yx}) - 1\}/n_1.$$

where

$$\delta_{pqm} = \mu_{pqm} / \left(\mu_{200}^{p/2} \mu_{020}^{q/2} \mu_{002}^{m/2} \right), \quad \mu_{pqm} = (1/N) \sum_{i=1}^N (y_i - \bar{Y})^p (x_i - \bar{X})^q (z_i - \bar{Z})^m,$$

(p, q, m) being non-negative integers.

To find the expectation and variance of $\hat{\rho}_{td}$, we expand $t(u, v, w, a)$ about the point $P = (1, 1, 1, 1)$ in a second-order Taylor's series, express this value and the value of r in terms of e 's. Expanding in powers of e 's and retaining terms up to second power, we have:

$$E(\hat{\rho}_{td}) = \rho_{yx} + o(n^{-1}) \quad (2.7)$$

which shows that the bias of $\hat{\rho}_{td}$ is of the order n^{-1} and so up to order n^{-1} , mean square error and the variance of $\hat{\rho}_{td}$ are same.

Expanding $(\hat{\rho}_{td} - \rho_{yx})^2$, retaining terms up to second power in e 's, taking expectation and using the above expected values, we obtain the variance of $\hat{\rho}_{td}$ to the first degree of approximation, as:

$$\begin{aligned} \text{Var}(\hat{\rho}_{td}) = \text{Var}(r) + \left(\rho_{yx}^2/n \right) & \left[C_x^2 t_1^2(P) + (\delta_{040} - 1)t_2^2(P) - At_1(P) \right. \\ & \left. - Bt_2(P) + 2\delta_{030}C_x t_1(P)t_2(P) \right] - \left(\rho_{yx}^2/n_1 \right) \left[C_x^2 t_1^2(P) + (\delta_{040} - 1)t_2^2(P) \right. \\ & \left. - C_z^2 t_3^2(P) - (\delta_{004} - 1)t_4^2(P) - At_1(P) - Bt_2(P) + Dt_3(P) + Ft_4(P) \right. \\ & \left. + 2\delta_{030}C_x t_1(P)t_2(P) - 2\delta_{003}C_z t_3(P)t_4(P) \right] \end{aligned} \quad (2.8)$$

where $t_1(P)$, $t_2(P)$, $t_3(P)$ and $t_4(P)$, respectively, denote the first partial derivatives of $t(u, v, w, a)$ respect to u, v, w and a , respectively, at the point $P = (1, 1, 1, 1)$, with

$$\text{Var}(r) = \left(\rho_{yx}^2/n \right) \left[\left(\delta_{220}/\rho_{yx}^2 \right) + (1/4)(\delta_{040} + \delta_{400} + 2\delta_{220}) - \{(\delta_{130} + \delta_{310})/\rho_{yx}\} \right] \quad (2.9)$$

$$A = \{ \delta_{210} + \delta_{030} - 2(\delta_{120}/\rho_{yx}) \} C_x,$$

$$B = \{ \delta_{220} + \delta_{040} - 2(\delta_{130}/\rho_{yx}) \},$$

$$D = \{ \delta_{201} + \delta_{021} - 2(\delta_{111}/\rho_{yx}) \} C_z,$$

$$F = \{ \delta_{202} + \delta_{022} - 2(\delta_{112}/\rho_{yx}) \}$$

Any parametric function $t(u, v, w, a)$ satisfying equation (2.6) and the conditions 1 and 2 can generate an estimator of the class equation (2.5).

The variance of $\hat{\rho}_{td}$ at equation (2.6) is minimized for:

$$\begin{aligned} t_1(P) &= \frac{[A(\delta_{040} - 1) - B\delta_{030}C_x]}{2C_x^2(\delta_{040} - \delta_{030}^2 - 1)} = \alpha(\text{say}), \\ t_2(P) &= \frac{(BC_x^2 - A\delta_{030}C_x)}{2C_x^2(\delta_{040} - \delta_{030}^2 - 1)} = \beta(\text{say}), \\ t_3(P) &= \frac{[D(\delta_{004} - 1) - F\delta_{003}C_z]}{2C_z^2(\delta_{004} - \delta_{003}^2 - 1)} = \gamma(\text{say}), \\ t_4(P) &= \frac{(C_z^2F - D\delta_{003}C_z)}{2C_z^2(\delta_{004} - \delta_{003}^2 - 1)} = \delta(\text{say}), \end{aligned} \tag{2.10}$$

Thus the resulting (minimum) variance of $\hat{\rho}_{td}$ is given by:

$$\begin{aligned} \min. \text{Var}(\hat{\rho}_{td}) &= \text{Var}(r) - \left(\frac{1}{n} - \frac{1}{n_1} \right) \rho_{yx}^2 \left[\frac{A^2}{4C_x^2} + \frac{\{(A/C_x)\delta_{030} - B\}^2}{4(\delta_{040} - \delta_{030}^2 - 1)} \right] \\ &\quad - \left(\rho_{yx}^2/n_1 \right) \left[\frac{D^2}{4C_z^2} + \frac{\{(D/C_z)\delta_{003} - F\}^2}{4(\delta_{004} - \delta_{003}^2 - 1)} \right] \end{aligned} \tag{2.11}$$

It is observed from equation (2.11) that if optimum values of the parameters given by (2.10) are used, the variance of the estimator $\hat{\rho}_{td}$ is always less than that of r as the last two terms on the right hand sides of (2.11) are non-negative.

Two simple functions $t(u, v, w, a)$ satisfying the required conditions are:

$$\begin{aligned} t(u, v, w, a) &= 1 + \alpha_1(u - 1) + \alpha_2(v - 1) + \alpha_3(w - 1) + \alpha_4(a - 1) \\ t(u, v, w, a) &= u^{\alpha_1} v^{\alpha_2} w^{\alpha_3} a^{\alpha_4} \end{aligned}$$

and for both these functions $t_1(P) = \alpha_1, t_2(P) = \alpha_2, t_3(P) = \alpha_3$ and $t_4(P) = \alpha_4$. Thus, one should use optimum values of $\alpha_1, \alpha_2, \alpha_3$ and α_4 in $\hat{\rho}_{td}$ to get the minimum variance.

It is to be noted that the estimated $\hat{\rho}_{td}$ attained the minimum variance only when the optimum values of the constants α_i ($i=1, 2, 3, 4$), which are functions of unknown population parameters, are known. To use such estimators in practice, one has to use some guessed values of population parameters obtained either through past experience or through a pilot sample survey. It may be further noted that even if the values of the constants used in the estimator are not exactly equal to their optimum values as given by equation (2.8) but are close enough, the resulting estimator will be better than the conventional estimator, as illustrated by Das and Tripathi (1978, Section 3).

If no information on second auxiliary variable z is used, then the estimator $\hat{\rho}_{td}$ reduces to $\hat{\rho}_{hd}$ defined in equation (2.2). Taking $z \equiv 1$ in equation (2.8), we get the variance of $\hat{\rho}_{hd}$ to the first degree of approximation, as:

$$\begin{aligned} \text{Var}(\hat{\rho}_{hd}) = \text{Var}(r) + \left(\frac{1}{n} - \frac{1}{n_1}\right) \rho_{yx}^2 \left[C_x^2 h_1^2(1, 1) + (\delta_{040} - 1) h_2^2(1, 1) \right. \\ \left. - Ah_1(1, 1) - Bh_2(1, 1) + 2\delta_{030} C_x h_1(1, 1) h_2(1, 1) \right] \end{aligned} \quad (2.12)$$

which is minimized for,

$$\begin{aligned} h_1(1, 1) &= \frac{[A(\delta_{040} - 1) - B\delta_{030}C_x]}{2C_x^2(\delta_{040} - \delta_{030}^2 - 1)}, \\ h_2(1, 1) &= \frac{(BC_x^2 - A\delta_{030}C_x)}{2C_x^2(\delta_{040} - \delta_{030}^2 - 1)} \end{aligned} \quad (2.13)$$

Thus the minimum variance of $\hat{\rho}_{hd}$ is given by:

$$\min. \text{Var}(\hat{\rho}_{hd}) = \text{Var}(r) - \left(\frac{1}{n} - \frac{1}{n_1}\right) \rho_{yx}^2 \left[\frac{A^2}{4C_x^2} + \frac{\{(A/C_x)\delta_{030} - B\}^2}{4(\delta_{040} - \delta_{030}^2 - 1)} \right] \quad (2.14)$$

It follows from equations (2.11) and (2.14) that

$$\min. \text{Var}(\hat{\rho}_{td}) - \min. \text{Var}(\hat{\rho}_{hd}) = \left(\rho_{yx}^2/n_1\right) \left[\frac{D^2}{4C_z^2} + \frac{\{(D/C_z)\delta_{003} - F\}^2}{4(\delta_{004} - \delta_{003}^2 - 1)} \right] \quad (2.15)$$

which is always positive. Thus, the proposed estimator $\hat{\rho}_{td}$ is always better than $\hat{\rho}_{hd}$.

3. A wider class of estimators

In this section, we consider a class of estimators of ρ_{yx} wider than equation (2.5) given by:

$$\hat{\rho}_{gd} = g(r, u, v, w, a) \quad (3.1)$$

where $g(r, u, v, w, a)$ is a function of r, u, v, w, a and such that

$$g(\rho, 1, 1, 1, 1) = \hat{\rho}_{td} \quad \text{and} \quad \left[\frac{\partial g(\cdot)}{\partial r} \right]_{(\rho, 1, 1, 1)} = 1$$

Proceeding as in Section 2, it can easily be shown, to the first order of approximation, that the minimum variance of $\hat{\rho}_{gd}$ is same as that of $\hat{\rho}_{td}$ given in equation (2.11).

It is to be noted that the difference-type estimator

$$r_d = r + \alpha_1(u - 1) + \alpha_2(v - 1) + \alpha_3(w - 1) + \alpha_4(a - 1),$$

is a particular case of $\hat{\rho}_{gd}$, but it is not the member of $\hat{\rho}_{td}$ in equation (2.5).

4. Optimum values and their estimates

The optimum values $t_1(P) = \alpha$, $t_2(P) = \beta$, $t_3(P) = \gamma$ and $t_4(P) = \delta$ given at equation (2.10) involve unknown population parameters. When these optimum values are substituted in equation (2.5), it no longer remains an estimator since it involves unknown $(\alpha, \beta, \gamma, \delta)$, which are functions of unknown population parameters, say, $\delta_{pqm}(p, q, m = 0, 1, 2, 3, 4)$, C_x , C_z and ρ_{yx} itself. Hence, it is advisable to replace them by their consistent estimates from sample values. Let $(\hat{\alpha}, \hat{\beta}, \hat{\gamma}, \hat{\delta})$ be consistent estimators of $t_1(P)$, $t_2(P)$, $t_3(P)$ and $t_4(P)$, respectively, where

$$\begin{aligned} \hat{t}_1(P) = \hat{\alpha} &= \frac{[\hat{A}(\hat{\delta}_{040} - 1) - \hat{B}\hat{\delta}_{030}\hat{C}_x]}{2\hat{C}_x^2(\hat{\delta}_{040} - \hat{\delta}_{030}^2 - 1)}, \\ \hat{t}_2(P) = \hat{\beta} &= \frac{[\hat{B}\hat{C}_x^2 - \hat{A}\hat{\delta}_{030}\hat{C}_x]}{2\hat{C}_x^2(\hat{\delta}_{040} - \hat{\delta}_{030}^2 - 1)}, \\ \hat{t}_3(P) = \hat{\gamma} &= \frac{[\hat{D}(\hat{\delta}_{004} - 1) - \hat{F}\hat{\delta}_{003}\hat{C}_z]}{2\hat{C}_z^2(\hat{\delta}_{004} - \hat{\delta}_{003}^2 - 1)}, \\ \hat{t}_4(P) = \hat{\delta} &= \frac{[\hat{C}_z^2\hat{F} - \hat{D}\hat{\delta}_{003}\hat{C}_z]}{2\hat{C}_z^2(\hat{\delta}_{004} - \hat{\delta}_{003}^2 - 1)}, \end{aligned} \tag{4.1}$$

with

$$\hat{A} = [\hat{\delta}_{210} + \hat{\delta}_{030} - 2(\hat{\delta}_{120}/r)]\hat{C}_x,$$

$$\hat{B} = [\hat{\delta}_{220} + \hat{\delta}_{040} - 2(\hat{\delta}_{130}/r)],$$

$$\hat{D} = [\hat{\delta}_{201} + \hat{\delta}_{021} - 2(\hat{\delta}_{111}/r)]\hat{C}_z,$$

$$\hat{F} = [\hat{\delta}_{202} + \hat{\delta}_{022} - 2(\hat{\delta}_{112}/r)],$$

$$\hat{C}_x = s_x / \bar{x},$$

$$\hat{C}_z = s_z / \bar{z},$$

$$\hat{\delta}_{pqm} = \hat{\mu}_{pqm} / \left(\hat{\mu}_{200}^{p/2} \hat{\mu}_{020}^{q/2} \hat{\mu}_{002}^{m/2} \right)$$

$$\hat{\mu}_{pqm} = (1/n) \sum_{i=1}^n (y_i - \bar{y})^p (x_i - \bar{x})^q (z_i - \bar{z})^m$$

$$\bar{z} = (1/n) \sum_{i=1}^n z_i,$$

$$s_x^2 = (n-1)^{-1} \sum_{i=1}^n (x_i - \bar{x})^2,$$

$$\bar{x} = (1/n) \sum_{i=1}^n x_i,$$

$$r = s_{yx} / (s_y s_x),$$

$$s_y^2 = (n-1)^{-1} \sum_{i=1}^n (y_i - \bar{y})^2,$$

$$s_z^2 = (n-1)^{-1} \sum_{i=1}^n (z_i - \bar{z})^2.$$

Finite correlation
coefficient

899

We then replace $(\alpha, \beta, \gamma, \delta)$ by $(\hat{\alpha}, \hat{\beta}, \hat{\gamma}, \hat{\delta})$ in the optimum $\hat{\rho}_{td}$ resulting in the estimator $\hat{\rho}_{td}^*$ say, which is defined by:

$$\hat{\rho}_{td}^* = rt^*(u, v, w, a, \hat{\alpha}, \hat{\beta}, \hat{\gamma}, \hat{\delta}), \quad (4.2)$$

where the function $t^*(U)$, $U = (u, v, w, a, \hat{\alpha}, \hat{\beta}, \hat{\gamma}, \hat{\delta})$ is derived from the function $t(u, v, w, a)$ given at equation (2.5) by replacing the unknown constants involved in it by the consistent estimates of optimum values. The condition (2.6) will then imply that

$$t^*(P^*) = 1 \quad (4.3)$$

where $P^* = (1, 1, 1, 1, \alpha, \beta, \gamma, \delta)$.

We further assume that

$$\begin{aligned}
 t_1(P^*) &= \left. \frac{\partial t^*(U)}{\partial u} \right]_{U=P^*} = \alpha, & t_2(P^*) &= \left. \frac{\partial t^*(U)}{\partial v} \right]_{U=P^*} = \beta \\
 t_3(P^*) &= \left. \frac{\partial t^*(U)}{\partial w} \right]_{U=P^*} = \gamma, & t_4(P^*) &= \left. \frac{\partial t^*(U)}{\partial a} \right]_{U=P^*} = \delta \\
 t_5(P^*) &= \left. \frac{\partial t^*(U)}{\partial \hat{\alpha}} \right]_{U=P^*} = 0, & t_6(P^*) &= \left. \frac{\partial t^*(U)}{\partial \hat{\beta}} \right]_{U=P^*} = 0 \\
 t_7(P^*) &= \left. \frac{\partial t^*(U)}{\partial \hat{\gamma}} \right]_{U=P^*} = 0, & t_8(P^*) &= \left. \frac{\partial t^*(U)}{\partial \hat{\delta}} \right]_{U=P^*} = 0
 \end{aligned}
 \tag{4.4}$$

Expanding $t^*(U)$ about $P^* = (1, 1, 1, 1, \alpha, \beta, \gamma, \delta)$, in Taylor's series, we have:

$$\begin{aligned}
 \hat{\rho}_{td}^* &= r[t^*(P^*) + (u - 1)t_1^*(P^*) + (v - 1)t_2^*(P^*) + (w - 1)t_3^*(P^*) \\
 &+ (a - 1)t_4^*(P^*) + (\hat{\alpha} - \alpha)t_5^*(P^*) + (\hat{\beta} - \beta)t_6^*(P^*) + (\hat{\gamma} - \gamma)t_7^*(P^*) \\
 &+ (\hat{\delta} - \delta)t_8^*(P^*) + \text{second order terms}]
 \end{aligned}
 \tag{4.5}$$

Using equation (4.4) in (4.5) we have:

$$\hat{\rho}_{td}^* = r[1 + (u - 1)\alpha + (v - 1)\beta + (w - 1)\gamma + (a - 1)\delta + \text{second order terms}] \tag{4.6}$$

Expressing equation (4.6) in term of e 's squaring and retaining terms of e 's up to second degree, we have:

$$(\hat{\rho}_{td}^* - \rho_{yx})^2 = \rho_{yx}^2 \left[\frac{1}{2}(2e_5 - e_0 - e_2) + \alpha(e_1 - e_1^*) + \beta(e_2 - e_2^*) + \gamma e_3^* + \delta e_4^* \right]^2 \tag{4.7}$$

Taking expectation of both sides in equation (4.7), we get the variance of $\hat{\rho}_{td}^*$ to the first degree of approximation, as:

$$\begin{aligned}
 \text{Var}(\hat{\rho}_{td}^*) &= \text{Var}(r) - \left(\frac{1}{n} - \frac{1}{n_1} \right) \rho_{yx}^2 \left[\frac{A^2}{4C_x^2} + \frac{\{(A/C_x)\delta_{030} - B\}^2}{4(\delta_{040} - \delta_{030}^2 - 1)} \right] \\
 &+ \left(\rho_{yx}^2/n_1 \right) \left[\frac{D^2}{4C_z^2} + \frac{\{(D/C_z)\delta_{003} - F\}^2}{4(\delta_{004} - \delta_{003}^2 - 1)} \right]
 \end{aligned}
 \tag{4.8}$$

which is same as equation (2.11), we thus have established the following result.

Result 4.1. If optimum values of constants in equation (2.10) are replaced by their consistent estimators and conditions (4.3) and (4.4) hold good, the resulting estimator $\hat{\rho}_{td}^*$ has the same variance to the first degree of approximation, as that of optimum $\hat{\rho}_{td}$.

Remark 4.1. It may be easily examined that some special cases:

- (1) $\hat{\rho}_{td1}^* = ru^{\hat{\alpha}}v^{\hat{\beta}}w^{\hat{\gamma}}a^{\hat{\delta}}$,
- (2) $\hat{\rho}_{td2}^* = r\{1 + \hat{\alpha}(u - 1) + \hat{\gamma}(w - 1)\} / \{1 - \hat{\beta}(v - 1) - \hat{\delta}(a - 1)\}$
- (3) $\hat{\rho}_{td3}^* = r[1 + \hat{\alpha}(u - 1) + \hat{\beta}(u - 1) + \hat{\gamma}(w - 1) + \hat{\delta}(a - 1)]$
- (4) $\hat{\rho}_{td4}^* = r[1 - \hat{\alpha}(u - 1) - \hat{\beta}(u - 1) - \hat{\gamma}(w - 1) - \hat{\delta}(a - 1)]^{-1}$

of $\hat{\rho}_{td}^*$ satisfy the conditions (4.3) and (4.4) and attain the variance (4.8).

Remark 4.2. The efficiencies of the estimators discussed in this paper can be compared for fixed cost, following the procedure given in Sukhatme *et al.* (1984).

5. Empirical study

To illustrate the performance of various estimators of population correlation coefficient, we consider the data given in Murthy (1967, p. 226). The variates are: y = output, x = number of workers, z = fixed capital, $N = 80$, $n = 10$, $n_1 = 25$,

$$\begin{aligned} \bar{X} &= 283.875, & \bar{Y} &= 5182.638, & \bar{Z} &= 1126, & C_x &= 0.9430, & C_y &= 0.3520, \\ C_z &= 0.7460, & \delta_{003} &= 1.030, & \delta_{004} &= 2.8664, & \delta_{021} &= 1.1859, & \delta_{022} &= 3.1522, \\ \delta_{030} &= 1.295, & \delta_{040} &= 3.65, & \delta_{102} &= 0.7491, & \delta_{120} &= 0.9145, & \delta_{111} &= 0.8234, \\ \delta_{130} &= 2.8525, & \delta_{112} &= 2.5454, & \delta_{210} &= 0.5475, & \delta_{220} &= 2.3377, & \delta_{201} &= 0.4546, \\ \delta_{202} &= 2.2208, & \delta_{300} &= 0.1301, & \delta_{400} &= 2.2667, & \rho_{yx} &= 0.9136, & \rho_{xz} &= 0.9859, \\ \rho_{yz} &= 0.9413. \end{aligned}$$

The percent relative efficiencies (PREs) of $\hat{\rho}_{1d}$, $\hat{\rho}_{hd}$, $\hat{\rho}_{td}$ with respect to conventional estimator r have been computed and compiled in Table I.

Table I clearly shows that the proposed estimator $\hat{\rho}_{td}$ (or $\hat{\rho}_{td}^*$) is more efficient than r and $\hat{\rho}_{hd}$.

Estimator	r	$\hat{\rho}_{hd}$	$\hat{\rho}_{td}$ (or $\hat{\rho}_{td}^*$)
PRE(., r)	100	129.147	305.441

Table I.
The PRE's of different estimators of ρ_{yx}

References

- Chand, L. (1975), "Some ratio-type estimators based on two or more auxiliary variables", PhD dissertation, Iowa State University, Ames, Iowa.
- Das, A.K. and Tripathi, T.P. (1978), "Use of auxiliary information in estimating the finite population variance", *Sankhya*, Ser. C, 40, pp. 139-48.
- Gupta, J.P. and Singh, R. (1989), "Usual correlation coefficient in PPSWR sampling", *Journal of Indian Statistical Association*, Vol. 27, pp. 13-16.
- Gupta, J.P., Singh, R. and Lal, B. (1978), "On the estimation of the finite population correlation coefficient-I", *Sankhya C*, Vol. 40, pp. 38-59.
- Gupta, J.P., Singh, R. and Lal, B. (1979), "On the estimation of the finite population correlation coefficient-II", *Sankhya C*, Vol. 41, pp. 1-39.
- Kiregyera, B. (1980), "A chain-ratio type estimators in finite population, double sampling using two auxiliary variables", *Metrika*, Vol. 27, pp. 217-23.
- Kiregyera, B. (1984), "Regression type estimators using two auxiliary variables and the model of double sampling from finite populations", *Metrika*, Vol. 31, pp. 215-26.
- Koop, J.C. (1970), "Estimation of correlation for a finite Universe", *Metrika*, Vol. 15, pp. 105-9.
- Murthy, M.N. (1967), *Sampling Theory and Methods*, Statistical Publishing Society, Calcutta, India.
- Rana, R.S. (1989), "Concise estimator of bias and variance of the finite population correlation coefficient", *Jour. Ind. Soc. Agr. Stat.*, Vol. 41 No. 1, pp. 69-76.
- Singh, S., Mangat, N.S. and Gupta, J.P. (1996), "Improved estimator of finite population correlation coefficient", *Jour. Ind. Soc. Agr. Stat.*, Vol. 48 No. 2, pp. 141-9.
- Srivastava, S.K. and Jhaji, H.S. (1986), "On the estimation of finite population correlation coefficient", *Jour. Ind. Soc. Agr. Stat.*, Vol. 38 No. 1, pp. 82-91.
- Sukhatme, P.V., Sukhatme, B.V., Sukhatme, S. and Asok, C. (1984), *Sampling Theory of Surveys with Applications*, Indian Society of Agricultural Statistics, New Delhi.
- Wakimoto, K. (1971), "Stratified random sampling (III): estimation of the correlation coefficient", *Ann. Inst. Statist. Math.*, Vol. 23, pp. 339-55.

Further reading

- Singh, R.K. (1982), "On estimating ratio and product of population parameters", *Cal. Stat. Assoc. Bull.*, Vol. 32, pp. 47-56.
- Srivastava, S.K. (1967), "An estimator using auxiliary information in sample surveys", *Cal. Stat. Assoc. Bull.*, Vol. 16, pp. 121-32.
- Srivastava, S.K. and Jhaji, H.S. (1983), "A class of estimators of the population mean using multi-auxiliary information", *Cal. Stat. Assoc. Bull.*, Vol. 32, pp. 47-56.
- Srivenkataremann, T. and Tracy, D.S. (1989), "Two-phase sampling for selection with probability proportional to size in sample surveys", *Biometrika*, Vol. 76, pp. 818-21.